









# NLS-NQUIRE500

# **CUSTOMER INFORMATION TERMINAL**

# **FEATURES**

# Advanced Technology

Armed with Newland's self-developed scan engine, the NLS-NQ500 can decode even poorer quality barcodes, such as soiled or wrinkled labels, with ease.

### O Diverse Functionalities.

NLS-NQ500 offers Bluetooth/ID/2D/WiFi/LAN functionalities to meet various application needs.

### Power Supply

Charged through power adapter or Power-over-Ethernet.

#### O External Device Connections

The external USB and GPIO ports enable the possibilities to attach a Newland handheld scanner for controlling an entry/exit gate or door lock.

# O Great Environment Adaption

Because of its small size and the VESA 75 mountability, it can be installed virtually anywhere in a store or office.

#### Excellent Product Interaction

Featuring a 5-inch HD screen (800x480 resolution), powered by Android 13 OS, and compatible with Newland MDM software















uch

# **NLS-NQUIRE500**

_					
Pe	40	N P	~~	TO.	00
гΘ	111	71	l e l e		

Processor 2.0GHz, octa-core 64-bit processor

Operating System Android 13 (can be upgrade to higher version)

Memory 4GB RAM/64GB ROM

Symbologies 2D Aztec, Composite, CS Code, Maxicode, Micro PDF, Micro QR, PDF 417, QR Code, Data Matrix,

DotCode.

1D Code128, Code 49, Code 16K, (GS1128) UCC/EAN-128, AIM-128, EAN-8, EAN-13, UPC-E, UPC-A,

ITF, ITF 6, ITF 14, Matrix 2 of 5, Industrial 25, Standard 2 of 5, Code39, ISSN, ISBN, CodaBar,

Code93, Code 11, Plessey, MSI Plessey, RSS.

Depth of Field EAN-13 70mm-610mm(13mil) (Depend on Barcode and Code39 110mm-290mm(5mil)

(Depend on Barcode and Environment)

PDF417 110mm-230mm(6.7mil)

Data Matrix 110mm-260mm(10mil)

QR Code 55mm-410mm(15mil)

#### Physical/Electrical

Dimensions (L×W×H)  $156.5(L) \times 100.4(W) \times 29(H)$  mm

Display 5" (854×480), capacitive touch screen
Keypad Up/down keys, Vol+/Vol-keys, Menu key

 Notification
 speaker and multi-color LEDs

 Sensor
 Gravity Sensor, infrared sensor

 GPS
 GPS (AGPS), GLONASS, Beidou, Galileo

Camera Front camera: 8 megapixels, Audio 1x Microphone, 2x Speakers  $8 \Omega / 1.5 W$ 

Interface USB 1x USB Type-C

Ethernet RJ45, support Power-over-Ethernet

Expansion 2x GPIO/1x expansion USB/2x series port

AC Adapter AC Adapter 12V@3A

POE IEEE 802.3 af/at

# **Environmental**

Operating Temperature  $-10^{\circ}\text{C} \text{ to } 50^{\circ}\text{C} \text{ (}14^{\circ}\text{F to } 122^{\circ}\text{F)}$ Storage Temperature  $-20^{\circ}\text{C} \text{ to } 60^{\circ}\text{C} \text{ (}-4^{\circ}\text{F to } 140^{\circ}\text{F)}$ Humidity 5% to 90% (non-condensing)

Static Discharge ±12 kV (Air discharge), ±6 kV (Direct discharge)

Sealing IP54 (front panel)

# NFC

13.56MHz RFID(Optional) ISO14443A/B, MIFARE, FeliCa, NFC Forum Tags, ISO15693

Support ID Card reading, support reader/writer mode

#### Wireless

WLAN RADIO Built-in 802.11 a/b/g/n/ac, support 2.4G and 5G dual frequency

WPAN RADIO Bluetooth 5.2

#### **Accessory (Optional)**

NFC antenna, MSR card reader

Specifications are subject to change without notice.

2024/02/06

Version: 1.4

#### **Newland AIDC**

Add: No.1 Rujiang West Rd., Mawei, Fuzhou, Fujian 350001, China Tel: +86-591-83979500 Fax: +86-591-83979216 Email: info@newlandaidc.com

Web: www.newlandaidc.com

Asia Pacific

Add: 6 Raffles Quay #14-06 Singapore 048582 Email: info@newlandaidc.com Europe & Middle East

Add: Rolweg 25, 4104 AV Culemborg, The Netherlands Tel: +31 (0) 345 87 00 33 Email: sales@newland-id.com Tech Support: tech-support@newland-id.com North America & Latin America

Add: 46559 Fremont Blvd., Fremont, CA 94538, USA Tel: +1 510 490 3888 Fax: +1 510 490 3887 Email: info@newlandaidc.com

